

LIGHT SWITCH SEALS

TOOLS NEEDED:



INSTRUCTION DETAILS:

1. Remove plate.
2. Punch out pre - cut hole in seal.
3. Place over receptacle / switch.
4. Replace plate.

For multi - switch boxes, trim seals to size with scissors. Tape together and install.



M-D Canada, a division of M-D Building Products

Headquarters

5720 Ambler Drive, Mississauga, ON, L4W 2B1
1-800-565-6653 | service@mdteam.com

Retail Distribution Center

2994 Peddie Rd, Unit 2, Milton, ON L9T 6Y9
1-888-908-1036 | retailorders@mdteam.com

ISOLANTS POUR INTERRUPTEURS D'ÉCLAIRAGE

OUTILS NÉCESSAIRES :



DÉTAILS POUR L'INSTALLATION :

1. Enlever la plaque.
2. Enfoncez le trou pré - coupé dans l'agent de scellement.
3. Placer sur l'articulation de l'interrupteur.
4. Remettre la plaque.

Pour les boîtes à plusieurs commutateurs, couper l'agent de scellement à la taille voulue avec des ciseaux. Coller ensemble et installer.



M-D Canada, une division de M-D Building Products

Siège social

5720 Ambler Drive, Mississauga (Ontario) L4W 2B1
1 800 565-6653 | service@mdteam.com

Centre de distribution au détail

2994 Peddie Road, Unit 2, Milton (Ontario) L9T 6Y9
1 888 908-1036 | retailorders@mdteam.com