

## LIGHT SWITCH SEALS

### TOOLS NEEDED:



### INSTRUCTION DETAILS:

1. Remove plate.
2. Punch out pre - cut hole in seal.
3. Place over receptacle / switch.
4. Replace plate.

For multi - switch boxes, trim seals to size with scissors. Tape together and install.



*M-D Canada, a division of M-D Building Products*

**Headquarters**

5720 Ambler Drive, Mississauga, ON, L4W 2B1  
1-800-565-6653 | [service@mdteam.com](mailto:service@mdteam.com)

**Retail Distribution Center**

2994 Peddie Rd, Unit 2, Milton, ON L9T 6Y9  
1-888-908-1036 | [retailorders@mdteam.com](mailto:retailorders@mdteam.com)

## ISOLANTS POUR INTERRUPTEURS D'ÉCLAIRAGE

### OUTILS NÉCESSAIRES :



### DÉTAILS POUR L'INSTALLATION :

1. Enlever la plaque.
2. Enfoncez le trou pré - coupé dans l'agent de scellement.
3. Placer sur l'articulation de l'interrupteur.
4. Remettre la plaque.

Pour les boîtes à plusieurs commutateurs, couper l'agent de scellement à la taille voulue avec des ciseaux. Coller ensemble et installer.



*M-D Canada, une division de M-D Building Products*

*Siège social*

5720 Ambler Drive, Mississauga (Ontario) L4W 2B1  
1 800 565-6653 | [service@mdteam.com](mailto:service@mdteam.com)

*Centre de distribution au détail*

2994 Peddie Road, Unit 2, Milton (Ontario) L9T 6Y9  
1 888 908-1036 | [retailorders@mdteam.com](mailto:retailorders@mdteam.com)